

## 160 METERS — 1.8-2.0 MHz

G	A	E	2.000	
█	█	█	1.999-2.000	Beacons
			1.995-2.000	Experimental
			1.910	QRP SSB Calling Frequency
			1.855	W1AW Voice
			1.843-2.000	SSB, SSTV and Wideband
			1.838	PSK31
			1.8175	W1AW Code
			1.810	QRP CW Calling Frequency
			1.800-1.810	Digital Modes

## 80/75 METERS — 3.5-4.0 MHz

T	G	A	E	4.000					
█	█	█	█	3.990	W1AW Voice				
				3.985	QRP SSB Calling Frequency				
				3.885	AM Calling Frequency				
				3.845	SSTV				
						<b>3.800</b>			
						<b>3.700</b>			
						<b>3.600</b>			
				█	█	█	█	3.5975	W1AW RTTY
								3.590	RTTY DX
								3.585-3.600	Automatically-controlled Data
3.5815	W1AW Code								
3.580	PSK31								
3.570-3.600	RTTY								
3.560	QRP CW Calling Frequency								
		<b>3.525</b>							
		3.500-3.510	CW DX Window						
		<b>3.500</b>							

## 60 METERS — 5 MHz, Channelized

G	A	E		
█	█	█	5.4035	5.405 MHz center frequency
			5.3715	5.373 MHz center frequency
			5.3665	5.368 MHz center frequency
			5.3465	5.348 MHz center frequency
			5.3305	5.332 MHz center frequency

50 watts PEP ERP maximum. Occupied bandwidth limited to 2.8kHz.

## 40 METERS — 7.0-7.3 MHz

T	G	A	E	7.300					
█	█	█	█	7.290	W1AW Voice				
				7.290	AM Calling Frequency				
				7.285	QRP SSB Calling Frequency				
						<b>7.175</b>			
						7.171	SSTV		
						<b>7.125</b>			
				█	█	█	█	7.100-7.105	Automatically-controlled Data
								7.095	W1AW RTTY
								7.080-7.125	RTTY
								7.070	PSK31
7.0475	W1AW Code								
7.040	QRP CW Calling/RTTY DX								
7.035	PSK31 (ITU Regions 1 & 3)								
		<b>7.025</b>							
		7.000-7.010	CW DX Window						
		<b>7.000</b>							

## 30 METERS — 10.1-10.15 MHz

G	A	E	10.150	
█	█	█	10.142	PSK31
			10.140-10.150	Automatically-controlled Data
			10.130-10.140	RTTY
			10.106	QRP CW Calling Frequency

200 watts PEP maximum.

█ CW, RTTY, Data, Phone, Image	T - Technician and Novice
█ CW, Phone, Image	G - General
█ CW, SSB Phone (200W PEP Max)	A - Advanced
█ CW, RTTY, Data	E - Amateur Extra
█ CW, RTTY, Data (200W PEP Max.)	
█ CW Only (200W PEP Max.)	
█ USB Phone Only	

## 20 METERS — 14.0-14.35 MHz

G	A	E	14.350					
█	█	█	14.290	W1AW Voice				
			14.286	AM Calling Frequency				
			14.285	QRP SSB Calling Frequency				
			14.230	SSTV				
					<b>14.225</b>			
					<b>14.175</b>			
					<b>14.150</b>			
			█	█	█	█	14.1005-14.112	Automatically-controlled Data
							14.100	Beacons
							14.095-14.0995	Automatically-controlled Data
14.095	W1AW RTTY							
14.070	PSK31							
14.070-14.095	RTTY							
14.060	QRP CW Calling Frequency							
14.0475	W1AW Code							
		<b>14.025</b>						
		<b>14.000</b>						

## 17 METERS — 18.068-18.168 MHz

G	A	E	18.168							
█	█	█	18.160	W1AW Voice						
					<b>18.110</b>					
			█	█	█	█	18.105-18.110	Automatically-controlled Data		
							18.1025	W1AW RTTY		
							18.100	PSK31		
							18.100-18.105	RTTY		
							18.0975	W1AW Code		
									<b>18.068</b>	

## 15 METERS — 21.0-21.45 MHz

T	G	A	E	21.450					
█	█	█	█	21.390	W1AW Voice				
				21.385	QRP SSB Calling Frequency				
				21.340	SSTV				
						<b>21.275</b>			
						<b>21.225</b>			
						<b>21.200</b>			
				█	█	█	█	21.150	Beacons
								21.095	W1AW RTTY
								21.090-21.100	Automatically-controlled Data
								21.070	PSK31
21.070-21.100	RTTY								
21.0675	W1AW Code								
21.060	QRP CW Calling Frequency								
		<b>21.025</b>							
		<b>21.000</b>							

## 12 METERS — 24.89-24.99 MHz

G	A	E	24.990	
█	█	█	24.930	Beacons
			24.925-24.930	Automatically-controlled Data
			24.920	PSK31
			24.920-24.925	RTTY

## 10 METERS — 28.0-29.7 MHz

T	G	A	E	29.700			
█	█	█	█	29.610-29.700	Repeater Outputs		
				29.600	FM Simplex		
				29.520-29.590	Repeater Inputs		
				29.300-29.510	Satellite Downlinks		
				29.000-29.200	AM		
				28.680	SSTV		
				28.590	W1AW Voice		
						<b>28.500</b>	
						28.385	QRP SSB Calling Frequency
						<b>28.300</b>	
█	█	█	█	28.200-28.300	Beacons		
				28.120	PSK31		
				28.120-28.189	Automatically-controlled Data		
				28.095	W1AW RTTY		
				28.070-28.150	RTTY		
				28.0675	W1AW Code		
				28.060	QRP CW Calling Frequency		
						<b>28.000</b>	